


PINE TECHNOLOGY USA
PT-604A

Data **bus:** 16-bit ISA
 Size: Half-length, full-height card
Hard drive supported: Two IDE (AT) Interface drives
Floppy drives supported: Two 360KB, 720KB, 1.2 MB, 1.44MB drives



CONNECTIONS		
Function	Location	
10-pin serial port internal	CN1	
10-pin serial port external	CN2	
25-pin parallel port external	CN3	
34-pin control cable connector floppy drive	CN4	
40-pin IDE (AT) interface connector	CN5	
16-pin game port internal	CN6	
2-pin connector - Drive active LED	JP10	

USER CONFIGURABLE SETTINGS			
Function	Location	Setting	
↔ Hard drive enabled	JPI	Pins 1 & 2 closed	
Hard drive disabled	JP1	Pins 2 & 3 closed	
↔ Floppy drive enabled	JP3	Pins 1 & 2 closed	
Floppy drive disabled	JP3	Pins 2 & 3 closed	
↔ Parallel Port IRQ7	IRQ	Pins 2 & 3 closed	
Parallel Port IRQ5	IRQ	Pins 1 & 2 closed	

Continued on next page ..

PINE TECHNOLOGY USA
PT-604A

continued from previous page

SERIAL PORTS INTERRUPT REQUEST					
Port 1	Port 1	JP2	JP5	JP7	JP8
COM1	COM2	Pins 1 & 2	Pins 1 & 2	Pins 1 & 2	Pins 1 & 2
COM1	COM4	Pins 1 & 2	Pins 1 & 2	Pins 2 & 3	Pins 1 & 2
COM3	COM2	Pins 1 & 2	Pins 1 & 2	Pins 1 & 2	Pins 2 & 3
COM3	COM4	Pins 1 & 2	Pins 1 & 2	Pins 2 & 3	Pins 2 & 3
COM1	Disabled	Pins 2 & 3	Pins 1 & 2	Pins 1 & 2	Pins 1 & 2
COM1	Disabled	Pins 2 & 3	Pins 1 & 2	Pins 2 & 3	Pins 1 & 2
COM1	Disabled	Pins 2 & 3	Pins 1 & 2	Pins 1 & 2	Pins 2 & 3
Disabled	COM2	Pins 1 & 2	Pins 2 & 3	Pins 1 & 2	Pins 1 & 2
Disabled	COM4	Pins 1 & 2	Pins 2 & 3	Pins 1 & 2	Pins 1 & 2
Disabled	COM2	Pins 1 & 2	Pins 2 & 3	Pins 1 & 2	Pins 2 & 3
Disabled	COM4	Pins 1 & 2	Pins 2 & 3	Pins 2 & 3	Pins 2 & 3
Disabled	Disabled	Pins 2 & 3	Pins 2 & 3	Pins 1 & 2	Pins 1 & 2
Disabled	Disabled	Pins 2 & 3	Pins 2 & 3	Pins 2 & 3	Pins 1 & 2
Disabled	Disabled	Pins 2 & 3	Pins 2 & 3	Pins 1 & 2	Pins 2 & 3
Disabled	Disabled	Pins 2 & 3	Pins 2 & 3	Pins 2 & 3	Pins 2 & 3

Note: Pins designated are closed.

PARALLEL PORT CONFIGURATION		
LPT	JP4	JP6
◊ LPT1	Pins 1 & 2 closed	Pins 1 & 2 closed
LPT2	Pins 2 & 3 closed	Pins 1 & 2 closed
Disabled	Pins 1 & 2 closed	Pins 2 & 3 closed
Disabled	Pins 2 & 3 closed	Pins 2 & 3 closed

FACTORY SETTINGS	
Jumper	Setting
JS1	N/A
JS2	N/A
JS3	N/A
JS4	N/A