

## Installing DRAM

### SIMM Banks

486-GVT can accommodate on-board memory from 1 to 96MB using SIMMs (Single-In-Line Memory Modules). The mainboard has three memory banks — Bank 0, 1, 2. Each bank can accept either a 256KB, 1MB, 4MB, or 16MB SIMM in each socket.

### DRAM Configuration

Memory can be installed in a variety of configurations, as shown in the next table:

TOTAL MEMORY	BANK 0 (30-PIN)	BANK 1 (72-PIN)	BANK 2 (72-PIN)
1MB	256K x 4		
		1M x 1	
			1M x 1
2MB	256K x 4	1M x 1	
		1M x 1	1M x 1
	256K x 4		1M x 1
3MB	256K x 4	1M x 1	1M x 1
4MB	1M x 4		
		4M x 1	
			4M x 1
5MB	256K x 4	4M x 1	
	256K x 4		4M x 1
	1M x 4	1M x 1	
	1M x 4		1M x 1
		1M x 1	4M x 1
		4M x 1	1M x 1

Table 3 - 1 DRAM Configurations