

## Addendum (SY-5SSM & SY-5SSM/5)

There is an error in the table on page 7 of the quick start guide. Please refer to this addendum for the correct content.

| Processor  | Voltage  | Voltage Setting: JP30 |       |       |       |       |
|--|--|-----------------------|-------|-------|-------|-------|
|  |  | 1-2                   | 3-4   | 5-6   | 7-8   | 9-10  |
| AMD K5 PR100<br>AMD K5 PR133<br>AMD K5 PR166   | 3.52 V   | open                  | short | short | short | short |
| The AMD K5 and K6 come in several versions with different voltages. Please verify the correct voltage settings with your dealer before installation. The most common K5 runs on 3.52V. |  |                       |       |       |       |       |
| AMD K6 166<br>AMD K6 200   | 2.9 V  | open                  | short | open  | open  | short |
| AMD K6 233   | 3.2 V  | open                  | short | short | open  | open  |
| AMD K6 266<br>AMD K6 300<br>AMD K6-2 266<br>AMD K6-2 300<br>AMD K6-2 333<br>AMD K6-2 350<br>AMD K6-2 366<br>AMD K6-2 380<br>AMD K6-2 400   | 2.2 V  | open                  | open  | open  | short | open  |
| AMD K6-2 450<br>AMD K6-2 475<br>AMD K6-2 500<br>AMD K6-III 400<br>AMD K6-III 450   | 2.4 V  | open                  | open  | short | open  | open  |
| Cyrix 6x86(L) PR166+<br>Cyrix 6x86(L) PR200+   | The Cyrix 6X86(L) and M6 come in several versions with different voltages. Please ask your dealer for the correct voltage. |                       |       |       |       |       |
| Cyrix 6x86MX PR166<br>Cyrix 6x86MX PR200<br>Cyrix 6x86MX PR233<br>Cyrix 6x86MX PR266<br>Cyrix MII 300<br>Cyrix MII 333<br>Cyrix MII 350<br>Cyrix MII 366<br>Cyrix MII 380              | 2.9 V  | open                  | short | open  | open  | short |
| Intel P54C P100<br>Intel P54C P133<br>Intel P54C P166<br>Intel P54C P200   | 3.3 V  | open                  | short | short | open  | short |
| The P54C (standard Pentium®) comes in several versions with different voltages. Please ask your dealer for the correct voltage. The most common P54C runs on 3.3V.                     |  |                       |       |       |       |       |
| Intel P55C P166<br>Intel P55C P200<br>Intel P55C P233  | 2.8 V  | open                  | short | open  | open  | open  |
| The P55C (MMX) processors have the same voltage setting.   |  |                       |       |       |       |       |

**990503**