

Addendum (FOR 5SSM)

AMD K6-2 450/475/500, K6-III 400/450 and Rise mP6 PR266 CPUs' Voltage and Frequency Setting.

Set JP30 for CPU Voltage

Processor	Voltage	Voltage Setting: JP30				
		1-2	3-4	5-6	7-8	9-10
AMD K6-2 450 AMD K6-2 475 AMD K6-2 500 AMD K6-III 400 AMD K6-III 450	2.4 V	open	open	short	open	open
Rise mP6 PR266	2.8 V	open	short	open	open	open

Set SW1,JP7,JP9 and JP10 for CPU Frequency

Processor	Bus Clock	Multi-plier	CPU Host Bus Setting: JP32				Frequency Multiplier: SW1		
			1-2	3-4	5-6	7-8	1-2	3-4	5-6
AMD K6-2 450	100MHz	4.5 x	open	open	short	short	short	short	short
AMD K6-2 475	95MHz	5.0 x	open	short	open	open	open	short	short
AMD K6-2 500	100MHz	5.0 x	open	open	short	short	open	short	short
AMD K6-III 400	100MHz	4.0 x	open	open	short	short	short	open	short
AMD K6-III 450	100MHz	4.5 x	open	open	short	short	short	short	short
Rise mP6 PR266	66MHz	3.0 x	open	short	short	short	open	short	open
	100MHz	2.0 x	open	open	short	short	short	open	open